# **CAVIUS**
























PRODUCT NAME: CAVIUS SMART REMOTE PRODUCT NUMBER: 9001

## **PRODUCT DATA:**

#### **DEVICE TYPE:**

Smart remote with emergency light.

#### **USAGE:**

Designed to alert with a rapid flashing warning light, vibration and buzzing when alarming and to remote control the CAVIUS Wireless alarms Family. Torch function to find escape routes at night.

#### **INSTALLATION POSITION:**

The body of the remote has a build-in magnet so that the remote can be installed on metal surfaces.

A lanyard can also be added to the end of the product so the remote can hang from a hook.

#### **PRODUCT DIMENSIONS:**

D: 58 mm x W: 140 mm

#### PRODUCT WEIGHT:

Base remote weight: 48 g.

#### **OPERATION AC/DC:**

DC

#### **BATTERY TYPE:**

3 x AAA batteries supplied with the Smart Remote.

#### LOW BATTERY INDICATION:

A short acoustic beep will sound to notify a low battery voltage.

#### INTERLINK FREQUENCY:

868 MHz. max 20mW

#### SIGNALS:

Transmits RF signals to the CAVIUS Wireless Family at alarm.

#### INTERLINK RANGE:

Minimum 100m in open field as a receiver, and within short range to silence an alarm. Range depends on the building materials and will need to be tested in each individual case.

#### SOUND:

Audible indicator.

#### **PUSH BUTTON:**

The Smart Remote is equipped with 3 switches:

Sliding learn switch to connect to other alarms in the wireless family

Test/hush button at the end. Torch button on the side.

#### WARRANTY:

10 year

#### **OPERATING TEMPERATURE:**

+4°C to +38°C

#### **OPERATING HUMIDITY:**

Up to 90% RH non-condensing

#### STORAGE TEMPERATURE:

-20°C to +60°C

#### STORAGE HUMIDITY:

Up to 93% RH non-condensing

## CONTACT

www.cavius.com

### **MANUFACTURER**

Carrier Fire & Security Danmark A/S

## CAVIUS



